



OPEN
Compute Project

Alpha Networks Inc.

STX-60x0-486F

48-port SFP+ with 6-port 100G QSFP28
(TOR/Aggregation Switch)

Author: Natalie Chang, Hook Wu



Revision History

Version	Revised Date	Author	Content Revised
0.1	01/19/2017	Natalie Chang	Initial Version



Scope

This documents defines the technical specification for STX-60x0-486F used in the Open Compute Project as 10G Top of the Rack (ToR) or as an aggregation switch

Contents

Revision History	2
Overview	6
License	6
1 Feature Highlights	8
2 Physical Overview	9
2.1 Mechanical Dimension	9
2.2 Top View	10
2.3 Front View	10
2.4 Rear View	10
3 LED Definition	10
4 Field Replaceable Components	12
4.1 Power Supply Modules	12
4.2 Fan Modules	16
5 System Overview	17
5.1 Main PCB	18
5.2 CPU Subsystem	19
5.2.1 Management CPU Board	20
5.2.2 PCIe Interface	22
5.2.3 Ethernet Port Connectivity for Broadwell DE CPU	23



5.2.4 Ethernet Port Connectivity for Rangeley CPU.....	24
5.2.5 UART Port Connectivity	24
6 IO and Connectors	25
6.1 USB Interfaces	25
7 Power/Environmental/Agency Certifications.....	25

List of Figures

Figure 1: STX-60x0-486F chassis dimension	9
Figure 2: STX-60x0-486F top view	10
Figure 3: STX-60x0-486F front view	10
Figure 4: STX-60x0-486F rear view	10
Figure 5: Power supply mechanical specification	14
Figure 6: Fan module mechanical specification.....	17
Figure 7: Main board block diagram.....	18
Figure 8: Main PCB top view.....	19
Figure 9: CPU module block diagram	20
Figure 10: PCIe connection.....	23
Figure 11: Ethernet port connection for Broadwell DE CPU.....	23
Figure 12: Ethernet port connection for Rangeley CPU.....	24
Figure 13: UART port connection	25

List of Tables

Table 1: LED behavior for system.....	11
Table 2: LED behavior for 10G & 100G Ethernet Port.....	12
Table 3: Power supply LED definition	12
Table 4: Power supplies usage	13
Table 5: Power supply connector pin out	14
Table 6: LED definition on power supply	14
Table 7: Power supply EEPROM FRU data format.....	16
Table 8: Fan modules part number.....	16
Table 9: Fan modules connector pin out	17
Table 10: PCBs for STX-60x0-486F	18
Table 11: CPU subsystem key Components	19
Table 12: Intel CPU module connector pin out.....	22
Table 13: Power consumption and environment table.....	26
Table 14: Regulatory standards compliance table	28



Overview

The STX-60x0-486F Series are leaf switch or aggregation switch for Data Center, Telco and Enterprise. It provides a total combined bandwidth of 2,160 Gbps, feature 48 ports of 10 Gbps with 6 ports of 100 Gbps at wire-speeds Ethernet. The system also provides a Mini-USB (Type B) console port and an out-of-band (OOB) management port.

The STX-60x0-486F switch supports 1+1 redundant power supplies and 5+1 redundant fan modules to provide the system reliability.

The CPU was designed as modules, and the following CPU modules are supported.

- Intel Rangeley CPU based (C2558, 4 cores/2.4GHz), model number: STX-60A0-486F
- Intel Broadwell DE CPU based (D1518, 4 cores/2.3GHz), model number: STX-60B0-486F

License

All semiconductor devices that may be referred to in this specification, or required to manufacture products described in this specification, will be considered referenced only, and no intellectual property rights embodied in or covering such semiconductor devices shall be licensed as a result of this specification or such references. Notwithstanding anything to the contrary in the CLA, the licenses set forth therein do not apply to the intellectual property rights included in or related to the semi-conductor devices identifies in the specification. These references include without limitation the reference to devices listed below. For clarity, no patent claim that reads on such semiconductor devices will be considered a “Granted Claim” under the applicable Contributor License Agreement for this specification.

Items		Detailed Description
MAC Controller		BCM88375*1
Packet DRAM		8GB
TCAM		NL88659 * 2
Octal Re-Timer		BCM82328*1
BMC		ASPEED AST1250*1
PHY for 100G		N/A, PHY-less design
MAC for Combo Management		Intel I210*1 BCM53115M*1
CPU Module for STX-60A0-486F		
Modular CPU board (option2)	CPU	Intel Rangeley C2558 Quad Cores/2.4GHz
	RAM	DDR3 4GB for Intel Rangeley CPU(reserved to 32GB)



Open Compute Project Alpha Networks STX-60x0-486F Specification v0.1

	Flash	M.2 SATA SSD 32GB for Intel Rangeley CPU(reserved to 64GB)
	Boot Flash	8MB for Intel Rangeley CPU(reserved to 16MB)
CPU Module for STX-60B0-486F		
Modular CPU board (option 1)	CPU	Intel Broadwell DE D-1518 Quad Cores/2.3GHz (Designed reserved up to 8 cores)
	RAM	DDR4 8GB (reserved up to TBD GB)
	Flash	M.2 SATA SSD 32GB for Intel Broadwell CPU (reserved up to TBD GB)
	Boot Flash	16MB for Intel Broadwell CPU(reserved to 32MB)

As of July 13, 2014, the following persons or entities have made this Specification available under the Open Compute Contributor License Agreement (OCP CLA) which is available at

<https://rightsignature.com/forms/OMMUS-72474399-v1-db5554/token/27cfcf4a00d>

Alpha Networks Inc.

*OCPHL - Permissive

You can review the signed copies of the Open Compute Contributor License Agreement for this Specification at <http://opencompute.org/licensing/>, which may also include additional parties to those listed above.

Your use of this Specification may be subject to other third party rights. THIS SPECIFICATION IS PROVIDED "AS IS." No support of any kind will be provided by the contributors. The contributors expressly disclaim any warranties (express, implied, or otherwise), including implied warranties of merchantability, non-infringement, fitness for a particular purpose, or title, related to the Specification. The entire risk as to implementing or otherwise using the Specification is assumed by the Specification implementer and user. IN NO EVENT WILL ANY PARTY BE LIABLE TO ANY OTHER PARTY FOR LOST PROFITS OR ANY FORM OF INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES OF ANY CHARACTER FROM ANY CAUSES OF ACTION OF ANY KIND WITH RESPECT TO THIS SPECIFICATION OR ITS GOVERNING AGREEMENT, WHETHER BASED ON BREACH OF CONTRACT, TORT (INCLUDING NEGLIGENCE), OR OTHERWISE, AND WHETHER OR NOT THE OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.



1 Feature Highlights

The STX-60x0-486F Series are leaf switch or aggregation switch for Data Center, Telco and Enterprise. It provides a total combined bandwidth of 2,160 Gbps, feature 48 ports of 10 Gbps with 6 ports of 100 Gbps at wire-speeds Ethernet. The system also provides a Mini-USB (Type B) console port and an out-of-band (OOB) management port.

- OCP micro server modular CPU board with large flash and memory
- Temperature warning via software-readable thermal monitor
- Real time clock (RTC) support
- Two Hot-swappable redundant power supply
- Six fan modules, (5+1) redundancy
- All I/O and management ports located on the front panels
- One R/J-45 GE out of band management port
- One Mini-USB (Type B) console port
- One USB (Type A) for storage device
- One reset button
- 48 port of SFP+ for 10Gbps Ethernet
- 6 port of QSFP28 for 100Gbps Ethernet

2 Physical Overview

2.1 Mechanical Dimension

Dimension	
Height x Width x Depth	44 mm (H) x 441 mm (W) x 487.4 mm(D)





Figure 1: STX-60x0-486F chassis dimension

2.2 Top View



Number	Items
1	Main Board
2	CPU Board
3	MGMT Board
4	LED Board
5	PSU Extender Board
6	Fan Extender Board
7	PSU x 2
8	FAN x 6

Figure 2: STX-60x0-486F top view

2.3 Front View




Figure 3: STX-60x0-486F front view

2.4 Rear View




Figure 4: STX-60x0-486F rear view

3 LED Definition

The following table defines the per device LEDs' behaviors:

Items	LED Indication	Color	Behavior	Description
-------	----------------	-------	----------	-------------

1	Locator	Blue	Blinking	Locator function is enable
			Off	Locator function is disable
2	STAT	Green	Solid Light	POST Passed, normal operation
			Blinking	POST in progress
			Light off	System No power
		Amber	Blinking	POST failed or overheat or power supply failed or Fan module fail or over temperature
			Solid Light	The Reset button is recessed
3	PWR	Green	Solid Light	Power On
			Off	Power Off and no power attached
		Amber	Blinking	Power supply failures, over voltage, over current, over temperature
4	FAN	Green	Solid Light	All diagnostics pass. The module is operational.
			Off	The module is not receiving power
		Amber	Blinking	Failure
5	MGMT Link	Green(R)	Solid Light	Link up
			Blinking	Packet transmitting or receiving
			Light off	No link up or port disable
6	MGMT Speed	Green(R)	Off	10M speed
			On	100M/1000G speed

Table 1: LED behavior for system

The following defines the 10G SFP+ and 100G QSFP28 Ethernet port LEDs' behaviors:

Location	LED Indication	Color	Behavior	Description
LED Port 1~48 (10G bps)	Link/Act/Speed	Green	Solid Light	A transceiver module or cable has been correctly installed. The port has a link and is operating at 10Gbps
			Blinking	The port is sending or receiving data at 10Gbps
		Amber	Solid light	A transceiver module or cable has been correctly installed. The port has a link and is operating at 1Gbps
			Blinking	The port is sending or receiving data at 1Gbps
		Off	Light off	Link down or no link
LED number	Link/Act/Speed	White	Solid Light	When there is a secure 100G connection (or link)

49~54, group of 1 (100Gbps)			Blinking	Packet transmitting or receiving
LED number 49~54, group of 1 (40Gbps)	Link/Act/Speed	Blue	Solid Light	When there is a secure 40G connection (or link)
			Blinking	Packet transmitting or receiving
LED number 49~54, group of 1 (50Gbps)	Link/Act/Speed	Amber	Solid Light	When there is a secure 50G connection (or link)
			Blinking	Packet transmitting or receiving
LED number 49~54, group of 1 (10G/25Gbps)	Link/Act/Speed	Green	Solid Light	When there is a secure 10G (40G Mode)/25G (100G Mode) connection (or link)
			Blinking	Packet transmitting or receiving
49~54, group of 1			Light off	No link up or port disable

Table 2: LED behavior for 10G & 100G Ethernet port

Each power supply module has a bi-color LED, which behavior is described in the following:

LED Color	Behavior	Description
Green	Solid Light	Output ON and OK
	Blinking	AC present / AC Line 12VSB Holdup
	Light off	No AC power to all power supplies
Amber	Solid Light	Power supply critical event causing a shutdown; failure, Fan Fail
	Blinking	Power supply warning events where the power supply continues to operate; high temp, high power, high current, slow fan.

Table 3: Power supply LED definition

4 Field Replaceable Components

4.1 Power Supply Modules

The switch is powered through one or two internal power supply modules.

Supported power supply modules:

- AC-770-12-FB
- AC-770-12-BF

- DC-1100-12-FB
- DC-1100-12-BF

The switch requires only one power supply for its operations, but you can include a second one for redundancy. By default the switch is installed one power supply in the second power supply slot, and filled the first slot with a filler panel. You can order extra power supplies with forward airflow or reverse airflow. Be sure to order the same direction of airflow as is used with the switch. Never leave a power supply slot empty. Please fill the slot with a filler panel.

Please refer to Table 4 for the recommended power supply usage for each switch model.

Switch Model Number	Equipped CPU Model	Power Supply Vendor	Power Supply Model Number	Minimum Number of Power Supply Need
STX-60A0-486F-AF-X	Intel Rangely C2558	Delta Electronics	AC-770-12-FB	1
STX-60A0-486F-AB-X	Intel Rangely C2558	Delta Electronics	AC-770-12-BF	1
STX-60A0-486F-DF-X	Intel Rangely C2558	Delta Electronics	DC-1100-12-FB	1
STX-60A0-486F-DB-X	Intel Rangely C2558	Delta Electronics	DC-1100-12-BF	1
STX-60B0-486F-AF-X	Intel Broadwell DE D-1518	Delta Electronics	AC-770-12-FB	1
STX-60B0-486F-AB-X	Intel Broadwell DE D-1518	Delta Electronics	AC-770-12-BF	1
STX-60B0-486F-DF-X	Intel Broadwell DE D-1518	Delta Electronics	DC-1100-12-FB	1
STX-60B0-486F-DB-X	Intel Broadwell DE D-1518	Delta Electronics	DC-1100-12-BF	1

Table 4: Power supplies usage

Power Supply connector: Molex 45984-4343

Pin #	Description	Pin #	Description
S1	+12VRS+	S13	N/A
S2	+12VRS-	S14	SGND
S3	12LS	S15	A0
S4	SMB ALERT	S16	N/A
S5	SDA	S17	Vs
S6	SCL	S18	N/A
S7	PSKILL	S19	N/A
S8	PSON	S20	N/A
S9	PWOK	S21	N/A

S10	A1	S22	N/A
S11	5VSB	S23	+5VSB
S12	5VSB	S24	+5BSB
P1	+12_VOUT	P3	GND
P2	+12_VOUT	P4	GND

Table 5: Power supply connector pin out




Figure 5: Power supply mechanical specification

LED definition on power supply

Power Supply Condition	LED Status
PSU is switched on and is running (Output ON and OK)	Green
No AC power to all power supplies or PSU is ON but with warning events	Off
PSU is OFF but 5VSB is on	1Hz on Blink Green
PSU critical event causing a shutdown: failure, OCP, OTP, OVP, UVP, Fan Fail	Amber
PSU warning events: high temp, high power, high current, slow fan, under input voltage	1Hz on Blink Amber

Table 6: LED definition on power supply

FRU

FRU data format compliant with IPMI version 1.0 (per rev 1.1 from Sept. 25, 1999) specification. The FRU device will implement the same protocols as the commonly used AT24C02 device, including the Byte Read, Sequential Read, Byte Write and Page Read protocols.

The EEPROM content is as following

Area Type	Description
Common Header	Format Version Number
Internal Use Area	Not required, do not reserve

Chassis Info Area	Not applicable, do not reserve
Board Info Area	Not applicable, do not reserve
Product Info Area	As defined by the IPMI FRU document. Product information is defined as following
Field name	Field Description
Manufacturer Name	{Formal name of manufacturer}
Product Name	{Manufacturer's model number}
Product part/model number	Customer part number
Product Version	Customer current revision
Product Serial Number	{Defined at time of manufacture}
Asset Tag	{Not used, code is zero length byte}
FRU File ID	{Not required}
PAD Bytes	{Added as necessary to allow for 8-byte offset to next area}
Mult-Record Area	As defined by the IPMI FRU documentation. The following information shall be used by this power supply: Power Supply Information (Record type 0x00) DC Output (Record Type 0x01) No other record types are required for power supply Multi-Record information shall be defined as following
Field Name (PS Info)	Field Information Definition
Overall Capacity (watts)	770
Peak VA	770
Inrush current (A)	40
Inrush interval (msec)	5
Low end input voltage range 1	100
High end input voltage range 1	127
Low end input voltage range 2	200
High end input voltage range 2	240
Low End Input Frequency Range	47
High End Input Frequency Range	63
Holdup Time (msec)	12

Binary flags	Set for: Hot Swap support, Auto switch and PFC
Peak Wattage	839 Watts
Peak Wattage Time in seconds	12
Combined wattage	770
Predictive fail tech support	Supported
Field Name (Output)	Field Description : Two output are to be defined from #1 to #2, as follows: +12V and +5VSB
Output Information	Set for: Standby on +5VSB, no 5VSB on all others
All other output fields	Format per IPMI specification , using parameters in this specification

Table 7: Power Supply EEPROM FRU data format

4.2 Fan Modules

The STX-60x0-486F supports up to 5+1 fan modules. For front to rear and rear to front air flow, different types of fan modules are required.

Air Flow Direction	Part Number
Front to Rear	AVC DFTA0456B2UP152
Rear to Front	AVC DFTA0456B2UP145

Table 8: Fan Modules part number

Fan module connector: LCU SM401V-20P

#	Name	Description	#	Name	Description
1	FAN_CON_TACH_0	FAN tachometer 0	11	FAN_DIR	FAN Direction
2	GND	GND	12	GND	GND
3	FAN_12VIN	12V	13	FAN_12VIN	12V
4	FAN_CON_PWM_0	PWM control for FAN0	14	EE_GND	EEPROM GND
5			15	EE_SDA	EEPROM SDA
6	EE_SCL	EEPROM SCL	16	EE_VDD	EEPROM VDD
7	EE_A0	EEPROM ADDR_0	17	FAN_CON_PWM_1	PWM control for FAN1
8	FAN_12VIN	12V	18	FAN_12VIN	12V
9	GND	GND	19	GND	GND
10	FAN_PRESENT#	Exist FAN module	20	FAN_CON_TACH_1	FAN tachometer 0

Table 9: Fan Modules connector pin out




Figure 6: Fan module mechanical specification

5 System Overview

The STX-60x0-486F comprised of the following PCB

PCB Function	PCB Layer	Dimension (L*W)mm
Main board	22	328.8mm*431.5mm
FAN module	2	38.5*29
FAN extend board	4	277*30
LED board	2	110.5*70
PSU board	4	41.3*132.4
CPU transfer board	4	223*16
CPU board (Rangeley)	12	210*90
CPU board (Broadwell DE)	12	210*100
Management board	2	112.1*57

Table 10: PCBs for STX-60x0-486F

5.1 Main PCB

The main PCB is a 22 layer PCB where the switch MAC resides. It also supports the following functions:

- Networking I/O ports
- Connectivity to Management ports
- LED
- Connectivity to power supply and fan
- Power conversion circuit
- Etc




Figure 7: Main board block diagram




Figure 8: Main PCB top view

5.2 CPU Subsystem

The following Table is the list of key components used in STX-60x0-486F

CPU Module for STX-60A0-486F		
Modular CPU board (option 2)	CPU	Intel Rangeley C2558 Quad Cores/2.4GHz
	RAM	DDR3 4GB for Intel Rangeley CPU(reserved to 32GB)
	Flash	M.2 SATA SSD 32GB for Intel Rangeley CPU(reserved to 64GB)
	Boot Flash	8MB for Intel Rangeley CPU(reserved to 16MB)
CPU Module for STX-60B0-486F		
Modular CPU board (option1)	CPU	Intel Broadwell DE D-1518 Quad Cores/2.3GHz (Designed reserved up to 8 cores)
	RAM	DDR4 8GB (reserved up to TBD GB)
	Flash	M.2 SATA SSD 32GB for Intel Broadwell CPU (reserved up to TBD GB)
	Boot Flash	16MB for Intel Broadwell CPU(reserved to 32MB)

Table 11: CPU subsystem key Components

5.2.1 Management CPU Board




Figure 9: CPU Module Block Diagram

Intel CPU module connector: x16 PCIe Edge Connector

For 80 PIN connector			
#	Pin Name	#	Pin Name
B1	P12V	A1	PRSNT#
B2	P12V	A2	P12V
B3	P12V	A3	P12V
B4	GND	A4	GND
B5	I2C_SCL	A5	RFU
B6	I2C_DATA	A6	RFU
B7	GND	A7	COM_TX
B8	PWR_BTN#	A8	COM_RX
B9	USB_P	A9	GE0_MDC
B10	USB_N	A10	GE0_MDIO

B11	SYS_RESET#	A11	PCIE0_RESET#
KEY			
B12	I2C_ALERT#	A12	GND
B13	GND	A13	PCIE0_REFCLK_P
B14	GND	A14	PCIE0_REFCLK_N
B15	PCIE0_TX0_P	A15	GND
B16	PCIE0_TX0_N	A16	GND
B17	GND	A17	PCIE0_RX0_P
B18	GND	A18	PCIE0_RX0_N
B19	PCIE0_TX1_P	A19	GND
B20	PCIE0_TX1_N	A20	GND
B21	GND	A21	PCIE0_RX1_P
B22	GND	A22	PCIE0_RX1_N
B23	PCIE0_TX2_P	A23	GND
B24	PCIE0_TX2_N	A24	GND
B25	GND	A25	PCIE0_RX2_P
B26	GND	A26	PCIE0_RX2_N
B27	PCIE0_TX3_P	A27	GND
B28	PCIE0_TX3_N	A28	GND
B29	GND	A29	PCIE0_RX3_P
B30	GND	A30	PCIE0_RX3_N
B31	UART0_TXD	A31	GND
B32	UART0_RXD	A32	GND
B33	GND	A33	RFU
B34	GND	A34	RFU
B35	PCIE1_REFCLK_P	A25	GND
B36	PCIE1_REFCLK_N	A36	GND
B37	GND	A37	RFU
B38	GND	A38	RFU
B39	PCIE1_RESET#	A39	GND
B40	RFU	A40	GND
B41	GND	A41	RFU
B42	GND	A42	NIC_SMBUS_ALERT#
B43	NIC_SMBUS_SCL	A43	GND
B44	NIC_SMBUS_SDA	A44	GND
B45	GND	A45	GE0_RX_P
B46	GND	A46	GE0_RX_N
B47	GE0_TX_P	A47	GND
B48	GE0_TX_N	A48	GND
B49	GND	A49	RFU
B50	GND	A50	RFU
B51	RFU	A51	GND

B52	RFU	A52	GND
B53	GND	A53	RFU
B54	GND	A54	RFU
B55	RFU	A55	GND
B56	RFU	A56	GND
B57	GND	A57	RFU
B58	GND	A58	RFU
B59	RFU	A59	GND
B60	RFU	A60	GND
B61	GND	A61	RFU
B62	GND	A62	RFU
B63	RFU	A63	GND
B64	RFU	A64	GND
B65	GND	A65	PCIE1_RX0_P
B66	GND	A66	PCIE1_RX0_N
B67	PCIE1_TX0_P	A67	GND
B68	PCIE1_TX0_N	A68	GND
B69	GND	A69	PCIE1_RX1_P
B70	GND	A70	PCIE1_RX1_N
B71	PCIE1_TX1_P	A71	GND
B72	PCIE1_TX1_N	A72	GND
B73	GND	A73	PCIE1_RX2_P
B74	GND	A74	PCIE1_RX2_N
B75	PCIE1_TX2_P	A75	GND
B76	PCIE1_TX2_N	A76	GND
B77	GND	A77	PCIE1_RX3_P
B78	GND	A78	PCIE1_RX3_N
B79	PCIE1_TX3_P	A79	GND
B80	PCIE1_TX3_N	A80	GND
B81	GND	A81	P12V
B82	GND	A82	P12V

Table 12: Intel CPU module connector pin out

5.2.2 PCIe Interface

PCI-Express Interface is used for management of the main board devices. They are connected as below.

CPU PCIe Lane 0-1: BCM88375

CPU PCIe Lane: I210




Figure 10: PCIe Connection

5.2.3 Ethernet Port Connectivity for Broadwell DE CPU

The Ethernet ports on the CPU are connected as follows:

CPU PCIe : MGMT Port

BMC MAC1 : MGMT Port




Figure 11: Ethernet Port Connection for Broadwell DE CPU

5.2.4 Ethernet Port Connectivity for Rangeley CPU

The Ethernet ports on the CPU are connected as follows:

CPU SGMII 0 :

CPU SGMII 1 : MGMT Port

CPU SGMII 2-3 :

CPU PCIe : MGMT Port

BMC MAC1 : MGMT Port




Figure 12: Ethernet Port Connection for Rangeley CPU

5.2.5 UART Port Connectivity

The Rangeley has two on-chip UART interfaces supporting RS232 serial ports. UART0 is unused and UART1 is used to drive the console port.

The first UART controllers (UART1) can be assigned to function as Host System COM port.

CPU UART0 : Reserved

CPU UART1 : Serial console port (mini USB Type B)




Figure 13: UART port connection

6 IO and Connectors

6.1 USB Interface

The CPU contains one Enhanced Host Controller Interface (EHCI) and complies to the EHCI 1.0 Specification. The EHCI supports up to four USB 2.0 root ports. USB 2.0 allows data transfers up to 480 Mbps. The controller integrates a Rate-Matching Hub (RMH) to support USB 1.1 devices. The USB Port 1 interface is configured by the debug software to be a debug port.

7 Power/Environmental/Agency Certifications

Power	
Number of power supply	2
Power supply types	AC (forward and reversed airflow) DC (forward and reversed airflow)
Typical operating power	377W
Maximum power	645W
AC PSUs	770W
• Input voltage	• 100 to 240 VAC
• Frequency	• 50 to 60 Hz
• Efficiency	
DC PSUs	1100W

<ul style="list-style-type: none"> • Input voltage range • Efficiency 	<ul style="list-style-type: none"> • 40.5V/23.8A 48V/19.0A -60V/15.6
Environment	
Operating temperature	0 ~ 45°C (at sea level with Fan Failure condition)
Altitude	0 ~ 10,000ft at 40°C*
Storage temperature	-40~70°C
Operating relative humidity	0%-95% RH (non-condensing)
Storage relative humidity	0%~95% RH (non-condensing)
Dimensions (height x width x depth)	44 mm (H) x 441 mm (W) x 487.4 mm(D)
Weight	TBD

Table 13: Power consumption and environment table

Regulatory Standards Compliance			
Regulatory compliance Safety		Comply with CE markings per directives 2004/108/EC and 2006/95/EC FCC/IC Report Class A BSMI UL/cUL Listed Mark CCC	
Safety		IEC60950-1 FCC/IC Report Class A EN 60950-1 FCC/IC Report Class A UL/CSA 60950-1 CNS 14336-1 GB4943.1	
EMC: Emissions		IEC60950-1 FCC/IC Report Class A EN 60950-1 FCC/IC Report Class A UL/CSA 60950-1 CNS 14336-1 GB4943.1	
RoHS Requirement			
Level	#	Description	Limitation / ppm
A	A1	Cadmium/ Cadmium Compounds	80
	A2	Hexavalent Chromium/ Hexavalent Chromium Compounds	800
	A3	Lead/ Lead Compounds	800
	A4	Mercury/ Mercury Compounds	800
	A5	Polybrominated Biphenyls (PBBs)	800
	A6	Polybrominated Diphenylethers (PBDEs)	800
Reliability Test Reports			
Test Items		Standards	Remarks

MTBF Prediction Report	Telcordia SR-332, Issue 2	
Free Fall Test Report	IEC 60068-2-32: Basic Environmental Testing Procedures Part 2: Tests Test Ed: Free Fall-Second Edition; Incorporating Amendment 1; Amendment 2: 10-1990	<ul style="list-style-type: none"> • Drop Range: \leq 20Kg, 1000mm; \leq 50kg, 500mm; • Max. Load: 500 kg; • FCS: 1 carton.
Vibration Test Report	IEC 60068-2-34:1973: Environmental testing Test Fd: Random vibration wide band-General requirements	<ul style="list-style-type: none"> • Frequency: 20Hz ~500Hz; • Method: Random; • Test Time: 30 min/Per Axis; • FCS: 1 carton.
Storage Test Report	IEC 60068-2-48: Basic Environmental Testing Procedures Part 2: Tests Guidance on the Application of the Tests of IEC Publication 68 to Simulate the Effects of Storage-First Edition	<ul style="list-style-type: none"> • Low Temp.: -40 °C, 72Hours • High Temp. /Low Humidity : 70 °C, 25%R.H., 72Hours • High Temp. /High Humidity : 40 °C, 95%R.H., 96Hours • FCS: 1 carton
Cold Test Report	IEC 60068-2-1: Environmental Testing Part 2: Tests - Tests A: Cold-Fifth Edition; Amendment 1-1993; Amendment 2-1994	<ul style="list-style-type: none"> • Temperature: -10\pm3 °C • Humidity: Uncontrolled • Test Time: 72 Hours • FCS: 2 sets
Dry Heat Cyclic Test Report	IEC 60068-2-2: Basic Environmental Testing Procedures Part 2: Tests - Tests B: Dry Heat-Fourth Edition; Supplement A-1976; Amendment 1-1993; Amendment 2-1994	<ul style="list-style-type: none"> • Temperature: 55\pm2 °C • Humidity: 5%R.H. • Test Time: 72 Hours • FCS: 2 sets
Damp Heat Steady State Report	IEC 60068-2-78: Environmental Testing - Part 2-78: Tests - Test 2-78: Body Cab: Damp Heat, Steady State-First Edition; (Replaces IEC 60068-2-3 and 60068-2-56)	<ul style="list-style-type: none"> • Temperature: 40\pm2 °C • Humidity: 95\pm2-3%R.H. • Test time: 96 Hours • FCS: 2 sets
Damp Heat Cyclic Report	IEC 60068-2-30: Basic Environmental Testing Procedures Part 2: Tests - Test Db and Guidance: Damp Heat, Cyclic	<ul style="list-style-type: none"> • Temperature: 40\pm2 °C • Humidity: 95\pm2-3%R.H. • Cycle Time: 24 Hours

	(12 + 12-Hour Cycle)-Second Edition; Amendment 1-08/1985	<ul style="list-style-type: none"> • Number of Cycle: 2 Cycles • FCS: 2 sets
ESD Simulation Test Report	IEC 61000-4-2: Electromagnetic Compatibility (EMC) - Part 4-2: Testing and Measurement Techniques - Electrostatic Discharge Immunity Test-Edition 1.2; Edition 1:1995 Consolidated with Amendments 1:1998 and 2:2000	<ul style="list-style-type: none"> • Air Discharge: $\pm 8\text{KV}$; • Contact Discharge: $\pm 4\text{KV}$; • FCS: 1 set.
Electrical Isolation Test Report	For Class I equipment only.	<ul style="list-style-type: none"> • Primary (L-N) to Earth (Metal frame or Ground Pin): Minimum 1,5 kV ac, at least 60 seconds; • Lan Port (RJ-45) to Ground (Metal frame) Minimum 1,5 kV ac at least 60 seconds.

Table 14: Regulatory Standards Compliance table